

Template for ordering	① 32	② 30S	③ E6	④ C-L / V-L	⑤ B1	Order Code	32-30S-E6-C-L/V-L-B1
Example	32 wide	30 series	Chant lock	Function: C / V lever / lever	Edge detail: B1	⑥ Handing	Right

① Specify plate width

* pricing as per price list

32 and 38 *(-1/-2 pricing)

44 and 50 *(-1B/-2B pricing)

② Length

10 Series (latching)	15 Series (44 min.) (privacy button)	20 Series (Short Euro / Cyl Plate)	30 Series (Euro / Cyl Plate)	40 Series (Euro / Cyl Plate)	60 Series (Tall) (Universal)	90 Series (Tilt & Turn)
112 +	112 +	175	191	220	300	231

Latch Function Only. Lever always positioned centrally.

32 / 38 only *(-3 pricing)

Plate and lock compatibility

10 / 15 Series	Latching only	30 Series	E4 - E7, O1 - O2	60 Series	E4 - E9, O2, MP (Multi-point)
20 Series	E1 - E4, O1	40 Series	E4 - E8, MP, O1 - O2	90 Series	TT only (Tilt & Turn)

NOTE: All plates can have latching function only.

③ Specify lever position / pitch or function (Y = Pitch. Specify any pitch not listed)

20S (short pitch Euro / Oval)	30S	40S	Multi-Point	Tilt & Turn
E1 P - 47.5mm (A = 54.5)	E4 P - 57mm (A = 61.5)	E4 P - 57mm (A = 79.5)	MP1 85mm	TT 92mm
E2 P - 48.5mm (A = 54.5)	E6 P - 72mm (A = 61.5)	E6 P - 72mm (A = 79.5)	MP2 85mm	
E4 P - 57mm (A = 54.5)	E7 P - 78mm (A = 61.5)	E7 P - 78mm (A = 79.5)		
E10 Please specify pitch	E10 Please specify pitch	E8 P - 85mm (A = 79.5)		
O1 P - 63.5mm (A = 120mm)	O2 P - 90mm (A = 138.5)	E10 Please specify pitch		

NOTE: Passage function levers require lock reference information as this detail determines lever position.

E1 Jackson, Yale 3100	E6 Chant, Hafele, Dorma, FSB, JADO	O1 Legge 990, Lockwood 3570	MP1 4 Point Lock
E2 Protector Series 735,	E7 Hafele Privacy	O2 Legge 995, Lockwood 5582, Lockwood 6582	MP2 2 Point Lock
E4 Baton lever/bolt	E8 Euro 85c, Optimum, Pentium, Pinnacle		

④ Select function

outside / back fix plates concealed fixing.				inside / surface fix plates semi concealed fixing.									
A	B	C	D	*E	*F	*G	H	R	S	T	U	*V	W
Passage	Passage	Euro	Oval	E-Turn	Recess E-Turn	Cyl Blank	Blank Oval Only	Euro Passage	Oval Passage	Euro	Oval	Thumb Turn	OZHLock

*These are drawn as Euro but (3) Lever position (lock type) code will determine the function position.

⑤ Select edge detail & profile

Example C1

Select from list, Standard or 'VED'

⑥ Choose handing

Please refer to chant handing sheet

Note: Singles are handed from the side of the door in which they are attached to.

